RF Media Converter

RFM–LC

Karakteristike

- **LoRaWAN EU 868Mhz na CAN Bus**
- LoRaWAN MAC verzija: V1.0
- Napajanje 12 do 24 V
- IP 25
- DIN montaža
- Platforma ASR6501

Opis uređaja

Uređaj služi kao LoRaWAN serijski RTU/ASCII na CAN bus gateway.
Jednostavna konfiguracija i upravljanje putem serijskog porta. Mogućnost povezivanja sa DATAMON cloud serverom.

Inova Tech d.o.o.
Ratka Mitrovica 130, 11090 Belgrade, tel: +381 11 63 100 26
office@inovatechit.com
wwww.inovatechit.com

Legal notice
Reproduction, transfer, distribution or storage of part or all of the contents in this document in any form without the prior written permission is prohibited. All rights reserved. All trademarks mentioned herein belong to their respective owners.
Copyright © 2021 Inova Tech

Specifikacija

Dimenzije: dužina 107 mm, širina 87,5 mm, visina 59 mm
Napon napajanja: 12V do 24V DC
Potrošnja: u stand by režimu 10mA
Setup protokol: UART AT komande 115200 8 N 1
Radio IC: SX1262
Master Chip: PSoC® 4000 series MCU (ARM® Cortex® M0+ Core)
Temperatura: -30°C do +70 °C
Modovi rada: Join mode ABP, OTAA
Klase rada: Class A , Class C
Sigurnosni protokoli: AES128
IP 25
Web OTA Wireless Upgrade
Serijski protokoli: CAN bus

Inova Tech d.o.o.
Ratka Mitrovica 130, 11090 Belgrade, tel: +381 11 63 100 26
office@inovatechit.com
wwww.inovatechit.com

Legal notice
Reproduction, transfer, distribution or storage of part or all of the contents in this document in any form without the prior written permission is prohibited. All rights reserved. All trademarks mentioned herein belong to their respective owners.
Copyright © 2021 Inova Tech